

# Induktive Näherungsschalter, 3-Draht

Inductive proximity switches, 3-wire  
 Finecorsa di prossimità induttivi, 3-fili  
 IFM IS5001



**EPP2I-7**  
**EPE2I-7**  
**EAP2I-7**  
**EAE2I-7**

## Varianten (Versions / Tipi)



Model EPP (S. 1)



Model EPE (S. 2)



Model EAP (S. 5)




Model EAE (S. 6)

## Technische Daten (Technical features / Dati tecnici)

<b>Endschalterfabrikat</b>	IFM
Producer switch / Marca finecorsa	
<b>Endschaltertyp</b>	IS5001 (3-wire, PNP)
Switch type / Tipo finecorsa	
<b>Spannung</b>	10-36V DC
Voltage / Tensione	
<b>Stromaufnahme</b>	0-200mA
Current / Corrente	
<b>Schaltfrequenz</b>	800Hz
Frequency / Frequenza	
<b>Leerlaufstrom</b>	15mA (24V)
No-load supply current / Corrente minima	
<b>Anzeige</b>	LED gelb (yellow / giallo)
Output indicator / Indicazione	
<b>Schutzart Schalter</b>	IP67 - DIN 40050
Enclosure switch / Protezione finecorsa	
<b>Temperatur</b>	-25°C ... +80°C
Temperature / Temperatura	

### Anschlussbild EP/EA

Connection / Connessione



## Adaption (Adoption / Adattamento)

Code code codice	Bohrbild Antrieb Hole spacing act. Foratura attuatore	Wellenhöhe Antrieb Shaft height act. Altezza perno att.	P = Polyamid Polyamide Poliammide	E = Edelstahl Stainless steel Acciaio Inox
00	50 x 25 mm	20 mm	x	x
01	80 x 30 mm	20 mm	x	x
02	80 x 30 mm	30 mm	x	x
03	130 x 30 mm	30 mm	x	x
04	130 x 30 mm	50 mm		x
05	80 x 30 mm	40 mm		x
06	80 x 30 mm	50 mm		x
07	130 x 30 mm	20 mm	x	x
08	130 x 30 mm	40 mm		x
09	50 x 25 mm	30 mm	x	x
10	Ohne Brücke Without bracket / Senza bracket			

### Schaltertyp

Switch type / Tipo finecorsa



## Artikelnummer (Code number / Numero codice)

Preisliste Seite 1 Price list page 1 / Listino dei prezzi pagina 1

